## ORION RANGE

## 'Orion' Range - OD100

## Infra-Red Motion Detector

- Wall Switch



Suitable for LED and energy saving lamps

Detection range 160°

Adjustable time delay

Adjustable ambient light

Built in replaceable fuse

PIR motion sensor

No neutral required



"Replaces standard light switch"



Model: OD100 - Function Switch:

'ON' = Permanently ON 'OFF' = Permanently OFF

'PIR" = PIR Control

Suitable for LED

Lamps

"Fits standard 25mm back box"

This product uses an Infra-Red heat detector.

The detector senses 'warmth movement' in the surrounding area when it is dark. When movement is detected the sensor is activated and triggers the connected load. It has a built in photo-cell that can identify day and night.

TECHNICAL INFORMATION	
Rated Voltage:	230V~50Hz
IP Rating:	IP20
Ambient Light:	<3-2,000 LUX (Adj)
Time Delay:	Min 10 sec ± 3 sec Max 7 min± 2 min
Rated Load:	0W - 500W -
	5W - 200W (LED
Detection Range:	160°
Detection Distance:	9M max (<24°C)
Working Temp:	-20° - + 40°C
Working Humidity:	<93%RH
Power Consumption:	0.5W approx
Installation Height:	1 - 1.8M
Detection Moving Speed: 0.6 - 1.5m/s	
Fuse Type:	3A, 20mm X 5mm
Dimensions:	80 x 80 x 44.1mm